

VISION Face Plates

DURAVISION
Pool Light products

TYPE RA

PZA100-RA-XX
PZA170-RA-XX



TYPE RN - thinner version of RA, suitable for concrete pools without liner

PZA100-RN-XX
PZA170-RN-XX



TYPE RB

PZA100-RB-XX
PZA170-RB-XX




TYPE RD

PZA100-RD-XX
PZA170-RD-XX



TYPE RF

PZA050-RF-XX
PZA100-RF-XX
PZA170-RF-XX



TYPE RO - thinner version of RF, suitable for concrete pools without liner

PZA050-RO-XX
PZA100-RO-XX
PZA170-RO-XX



TYPE RP - suitable for concrete pools, in combination with WC or WCS Wall Conduit

PZA100-RP-SS



Scan or click here for the online installation manuals.

TECHNICAL SPECIFICATIONS

CHARACTERISTICS	UNIT	PZA100-RA-XX	PZA170-RA-XX
Colour - (XX)		WH DG LG LB SW BL SS	WH DG LG LB SW BL SS
For lamp diameter	mm	100	170
Outer diameter	mm	180	250
Thickness	mm	21	21

CHARACTERISTICS	UNIT	PZA100-RN-XX	PZA170-RN-XX
Colour - (XX)		WH DG LG LB SW BL SS	WH DG LG LB SW BL SS
For lamp diameter	mm	100	170
Outer diameter	mm	160	250
Thickness	mm	13	12

CHARACTERISTICS	UNIT	PZA100-RB-XX	PZA170-RB-XX
Colour - (XX)		WH DG LG LB SW BL	WH DG LG LB SW BL
For lamp diameter	mm	100	170
Outer diameter	mm	175	270
Thickness	mm	21	21

CHARACTERISTICS	UNIT	PZA100-RD-XX	PZA170-RD-XX
Colour - (XX)		WH DG LG LB MB SW BL SS	WH DG LG LB MB SW BL SS
For lamp diameter	mm	100	170
Outer diameter	mm	175	250
Thickness	mm	20	21

CHARACTERISTICS	UNIT	PZA050-RF-XX	PZA100-RF-XX	PZA170-RF-XX
Colour - (XX)		WH DG LG LB BL SS	WH DG SS	WH DG SS
For lamp diameter	mm	50	100	170
Outer diameter	mm	128	185	280
Thickness	mm	18	20	21

CHARACTERISTICS	UNIT	PZA050-RO-XX	PZA100-RO-XX	PZA170-RO-XX
Colour - (XX)		WH DG LG LB BL SS	SS	SS
For lamp diameter	mm	50	100	170
Outer diameter	mm	100	170	270
Thickness	mm	9	13	16

CHARACTERISTICS	UNIT	PZA100-RP-SS
Colour - (SS)		SS
For lamp diameter	mm	100
Outer diameter	mm	140
Thickness	mm	15

- WH White
- LB Light blue
- SW Sand white
- DG Dark grey
- MB Navy blue
- BL Black
- LG Light grey
- CG Caribbean green
- SS Stainless steel

Replace -XX with colour code to obtain the correct order code.
Example: PZA100-RA-WH